

GatLing500	10CH Mode1&2	Dmx Value	Function
Dimmer	1	0--255	Darkness----->Brightness
Color	2	0---40 41---81 82---122 123---163 164---204 205---255	White Color1 Color2 Color3 Color4 Color5
CTC	3	0---255	EXCLUDED--->INSERTED
Gobo	4	1---40 42---81 83---122 124---163 165---204 205---255	White Gobo1 Gobo2 Gobo3 Gobo4 Gobo5
IRIS	5	0---127 128---255	EXCLUDED INSERTED
Frost	6	0---127 128--255	EXCLUDED INSERTED
Zoom	7	0---255	
Focus	8	0---255	
Lamp Control	9	0---255	Reserved
Control	10	0---231 232---255	Reserved Reset ALL(> 3s)